

# Kabeltabelle Koaxialkabel sortiert nach Kabeltyp

Kabeltyp	Kabelgruppe	Ø
0.3/1.95D/3.7 <sup>2</sup>	63	4
0.3L/1.85/3	55	3
0.36L/1.5/2.8	79	3
0.4/2/3.6	56	4
0.4/2.5D/4.8 Draka <sup>2</sup>	47	5
0.41/1.9AF/3.1 Draka	74	4
0.45/1.95AF/3.4	76	4
0.45/2/3.6	56	4
0.5/2.3/3.9	45	4
0.5/3.0D/5.6 <sup>2</sup>	70	6
0.5L/2.6/3.9	45	4
0.54L/2.2/3.5	76	4
0.54L/2.3/3.1 Leoni	67	4
0.58/2.6 AF/4.0	71	4
0.58/2.6(2 AF)D/4.7	83	5
0.6/1.2/2	53	2
0.6/2.8/5	19	5
0.6/2.8 AF Draka	42	5
0.6/2.8 AF/6.1	32	6
0.6/3.7	23	6
0.6/3.7/6.7 Sony	69	6
0.6/3.7/6.8	38	7
0.6/3.7D/8.6 Siemens <sup>2</sup>	62	9
0.6/4.0/8 (93Ω)	57	8
0.6L/3.7D/7 <sup>2</sup>	38	7
0.64L/2.8/3.9 Raychem	41	4
0.7/4.5/6.7 Pope	37	6
0.7L/4.3/6.4	54	6
0.75L/3.2/4.5 Perivox	61	5
0.75L/3.2/6.0 Perivox	73	6
0.75L/3.2 AF/4.4 Leoni	88	5
0.75L/3.2 AF/4.8	84	5
0.78L/4.9/7.6 Canare	65	7
0.8/3.7/6	50	6
0.8/3.7 AF Draka	50	6
0.8/3.7 AF/7.3	33	7
0.8/3.7D <sup>2</sup>	92	6
0.8L/3.7D <sup>2</sup>	92	6
0.8/4.9D <sup>2</sup>	11	7
0.95/4.8/7 <sup>3</sup>	51	7
1.0/4.8/7 <sup>3</sup>	51	7
1.0/4.8 AF Draka	51	7

Kabeltyp	Kabelgruppe	Ø
1.0/4.8 AF/8.6	34	9
1.0L/2.95/4.1	48	4
1.0L/4.8D Draka <sup>2</sup>	93	7
1.0/6.6	13	9
1.0/6.6D/10.1 <sup>2</sup>	36	11
1.13/4.8/6.6 (Wisi MK 90)	58	7
1.13/4.8/7	58	7
1.2L/4.8Dz Draka <sup>2</sup>	94	7
1.2L/4.95 AF Draka	58	7
1.4/6.6 AF Draka	52	9
1.4/6.6 AF/10.4	35	11
1.4L/3.7/5.5 Alcatel	72	6
1.45L/6.3D/9.3 Siemens <sup>2</sup>	66	9
1.6/7.2/10	60	11
1.6/7.3 AF Draka	60	11
1.6/7.5/10.4	43	11
1.9/6.9CuF/10.4	80	11
1.9L/4.9CuF/7.3	78	7
2.7/7.3 AF	68	11
ULTRA HD PRO 50 UHD Draka	91	5
ULTRA HD PRO 100 UHD Draka	58	7
<b>RG-Kabel</b>		
RG-5B	14	9
RG-6A	12	8
RG-6A mit Ø 8,7	77	9
RG-8A	27	11
RG-9B	27	11
RG-11A	28	11
RG-13A	28	11
RG-55	5	5
RG-55A	5	5
RG-55B	5	5
RG-58	5	5
RG-58A	5	5
RG-58C	5	5
RG-59	23	6
RG-59A	23	6
RG-59B	23	6
RG-62	8	6
RG-62A	8	6
RG-62B	8	6

# Kabeltabelle Koaxialkabel sortiert nach Kabeltyp

Kabeltyp	Kabelgruppe	Ø
RG-62C	8	6
RG-63B	29	11
RG-71	23	6
RG-71A	23	6
RG-71B	23	6
RG-115A	27	11
RG-122	3	4
RG-133	29	11
RG-140	23	6
RG-141	5	5
RG-141A	5	5
RG-142	5	5
RG-142A	5	5
RG-142B	5	5
RG-143A	14	9
RG-144	60	11
RG-149	28	11
RG-161	2	3
RG-165	27	11
RG-174	1	3
RG-178A	2	3
RG-178B	46	2
RG-179A	1	3
RG-179B	2	3
RG-179DT <sup>3</sup>	79	3
RG-180	4	4
RG-180A	4	4
RG-180B	4	4
RG-187A	2	3
RG-188A	1	3
RG-195	4	4
RG-195A	4	4
RG-196A	46	2
RG-210	8	6
RG-212	14	9
RG-213	27	11
RG-214	27	11
RG-216	28	11
RG-21A	14	9
RG-222	14	9
RG-223	64	5
RG-225	27	11

Kabeltyp	Kabelgruppe	Ø
RG-302	23	6
RG-303	5	5
RG-304	22	7
RG-316	1	3
<b>Beldenkabel</b>		
1406B <sup>3</sup>	75	4
1505A <sup>3</sup>	50	6
1505ANH <sup>3</sup>	50	6
1505F <sup>3</sup>	92	6
1520A <sup>3</sup>	2	3
1521A <sup>3</sup>	2	3
1522A <sup>3</sup>	2	3
1694A <sup>3</sup>	51	7
1694ANH <sup>3</sup>	51	7
1694F <sup>3</sup>	93	7
1794A <sup>3</sup>	87	8
1855A <sup>3</sup>	71	4
1855ENH <sup>3</sup>	42	5
1865A <sup>3</sup>	45	4
43187 <sup>2+3</sup>	38	7
46067 <sup>3</sup>	23	6
46899 <sup>3</sup>	42	5
70080CH <sup>3</sup>	42	5
7710A <sup>3</sup>	51	7
7711A <sup>3</sup>	51	7
7712A <sup>3</sup>	51	7
7713A <sup>3</sup>	51	7
7731A <sup>3</sup>	60	11
7731ANH <sup>3</sup>	60	11
7796A <sup>3</sup>	50	6
8213 <sup>3</sup>	60	11
8238 <sup>3</sup>	60	11
8241 <sup>2+3</sup>	23	6
8281 <sup>2+3</sup>	12	8
9244 <sup>3</sup>	23	6
9248 <sup>3</sup>	51	7
9259 <sup>3</sup>	50	6
9265 <sup>3</sup>	50	6
<sup>2</sup> Doppelschirmkabel <sup>3</sup> Beldenkabel Einteilung nach Abmessungen - nicht nach Wellenwiderstand.		

Irrtümer und Fehler vorbehalten.